

RH Series Power Relays

SPDT through 4PDT, 10A contacts Midget power relays

The RH series are miniature power relays with a large capacity. The RH relays feature 10A contact capacity as large as the RR series and the same size as IDEC's miniature relays. The compact size saves space.



| Termination | Style | SPDT | | DPDT | | | |
|-------------------|---|-------------------------|---|--|--|-------------------------|----------------------------------|
| | | Part No. | Coil Voltage Code * | Part No. | Coil Voltage Code * | | |
| Plug-in Terminal | Basic | RH1B-U* RH1B-UW* | AC6, AC12, AC24, AC50, AC100, AC110, AC115, AC120, AC200, AC220, AC230, AC240 DC6, DC12, DC24, DC48, DC100, DC110 | RH2B-U* RH2B-UW* | AC6, AC12, AC24, AC50, AC100-110, AC110-120, AC200-220, AC220-240 DC6, DC12, DC24, DC48, DC100-110 | | |
| | With Indicator | RH1B-UL* RH1B-ULW* | | RH2B-UL* RH2B-ULW* | | | |
| | With Check Button | — | | RH2B-UC* | | | |
| | With Indicator and Check Button | — | | RH2B-ULC* | | | |
| | Top Bracket Mounting | RH1B-UT* RH1B-UTW* | | RH2B-UT* RH2B-UTW* | | | |
| | With Diode (DC coil only) | RH1B-UD* RH1B-UDW* | | DC6, DC12, DC24, DC48, DC100, DC110 | | RH2B-UD* RH2B-UDW* | DC6, DC12, DC24, DC48, DC100-110 |
| | With Indicator and Diode (DC coil only) | RH1B-ULD* RH1B-ULDW* | | — | | RH2B-ULD* RH2B-ULDW* | |
| PC Board Terminal | Basic | RH1V2-U* RH1V2-UW* | AC6, AC12, AC24, AC50, AC100, AC110, AC115, AC120, AC200, AC220, AC230, AC240 DC6, DC12, DC24, DC48, DC100, DC110 | RH2V2-U* RH2V2-UW* | AC6, AC12, AC24, AC50, AC100-110, AC110-120, AC200-220, AC220-240 DC6, DC12, DC24, DC48, DC100-110 | | |
| | With Indicator | — | — | RH2V2-UL* RH2V2-ULW* | | | |
| | With Diode (DC coil only) | RH1V2-UD* RH1V2-UDW* | DC6, DC12, DC24, DC48, DC100 | RH2V2-UD* RH2V2-UDW* | DC6, DC12, DC24, DC48, DC100-110 | | |

• Part number ending with W is cadmium free.

Part No. Development

When ordering, specify the Part No. and coil voltage code.

(Example) **RH2B-U** **AC100-110**
 Part No. Coil Voltage Code